


Fuse Link & Holder



Fuse Holder Without LED LRT18B

Indicator	Rated Current In(A)	Type Designation	Pole No.	Article No.
without	20	LRT18BS20	1	LRT18B01
without	20	LRT18BD20	2	LRT18B02
without	20	LRT18BT20	3	LRT18B03
without	20	LRT18BF20	4	LRT18B05
without	32	LRT18BS32	1	LRT18B06
without	32	LRT18BD32	2	LRT18B07
without	32	LRT18BT32	3	LRT18B08
without	32	LRT18BF32	4	LRT18B09
without	63	LRT18BS63	1	LRT18B10
without	63	LRT18BD63	2	LRT18B11
without	63	LRT18BT63	3	LRT18B12
without	63	LRT18BF63	4	LRT18B13
without	125	LRT18BS125	1	LRT18B14
without	125	LRT18BD125	2	LRT18B15
without	125	LRT18BT125	3	LRT18B16
without	125	LRT18BF125	4	LRT18B17

Technical Data

Fuse Base LRT18B

- This series fuse is suitable for AC 50Hz, raged voltage to 690V, rated current to 125A.
- It is mainly used for protecting the electrical circuit against overload and short-circuits(gG/gL).
- It also may derive for protecting the semiconductor device and others complete set installment from short-circuit(aR) as well as the electric motor from short-circuit(aM).

Electrical

Design according to : IEC 60269
 Rated voltage : 500V
 Rated current : 20A,32A,63A,125A
 Working Frequency : AC 50Hz
 Breaking Capacity : 100kA

Dimensions(mm)

