

Motor Protective Devices

Magnetic Starter



Magnetic Starter LNJ1

Setting Range(A)	Type Designation	Article No.
9	LNJ109	J101
9	LNJ109	J102
12	LNJ112	J103
18	LNJ118	J104
25	LNJ125	J105
25	LNJ125	J106
32	LNJ132	J107
40	LNJ140	J108
40	LNJ140	J109
50	LNJ150	J110
50	LNJ150	J111
65	LNJ165	J112
80	LNJ180	J113
80	LNJ180	J114
95	LNJ195	J115

Technical Data

Magnetic Starter - LNJ1

- LNJ1 series magnetic starter is mainly applied to circuit of AC 50 or 60Hz, voltage up to 550V
- For far distance making and breaking circuit and frequently starting and controlling motor
- It has the features of small volume, light weight, low power consumption, high efficiency, safe and reliable performance etc.

Electrical

Type Designation	Maximum power AC3 duty (KW)					
	220V , 230V	380V , 400V	415V	440V	500V	660V , 690V
LNJ109	2.2	4	4	4	5.5	5.5
LNJ112	3	5.5	5.5	5.5	7.5	7.5
LNJ118	4	7.5	9	9	10	10
LNJ125	5.5	11	11	11	15	15
LNJ132	7.5	15	15	15	18.5	18.5
LNJ140	11	18.5	22	22	22	30
LNJ150	15	22	25	30	30	33
LNJ165	18.5	30	37	37	37	37
LNJ180	22	37	45	45	55	45
LNJ195	25	45	45	45	55	45

Dimensions(mm)

